

Engineered Electronics, Inc
 4301 Industrial Access Road
 Douglasville, GA 30134
 THREE AUDIO VISUAL PATIENT STATION WITH
 ONE ASSOCIATED EMERGENCY DEVICES
 SIZE **A** DRAWING NO. **103-010** DATE **10-03-03**

FIELD CONNECTION WIRES ——— 18 GAGE
 POINT WIRES ——— 22 GAGE
 STATION WIRES ——— 22 GAGE
 AUDIO WIRES ——— 22 GAGE

IMPORTANT
 SHIELD
 TIE TOGETHER AND TAPE AUDIO SHIELDS AT
 ALL JUNCTIONS POINTS AND CONNECT ONLY
 TO SHIELD (SH) TERMINAL IN CONTROL PANEL.

NOTE!
 RUNS OVER 750 FT INCREASE FIELD CONNECTION
 WIRES AND POINT WIRES ONE GAGE SIZE.

A CONNECTOR IS SUPPLIED
 WITH EACH PATIENT STATION.
 WIRES NOT USED MUST BE
 ELECTRICALLY ISOLATED

900-154

IT IS RECOMMENDED THAT A FIELD CONNECTION
 CABLE RUN FROM THE CONTROL PANEL BE LOOPED
 DOME LIGHT JUNCTION BOX TO DOME LIGHT JUNCTION
 BOX FOR EACH SIDE OF A HALLWAY.

POINTS (1-80)
 900-203
 CONTROL PANEL

SHIELD
 AUDIO
 AUDIO
 ALL CALL
 EMERGENCY LOW
 CHASSIS GROUND
 GROUND
 ROOM COMMON
 + 24 FLD

FIELD CONNECTIONS
 900-203 CONTROL PANEL

